

AXIS Entry Manager

Easy access management powered by IP

AXIS Entry Manager is a web-based software solution developed specifically for access control for small systems with basic needs. It comes pre-loaded on AXIS A1001 Network Door Controller and is used for installation, configuration, and administration of credentials. Being a fully distributed solution, all data is stored in the controllers and the system can be managed from any computer on the network. The system is completed with standard IT equipment, readers, door locks and door position sensors that meet the installation requirements.

- > **Pre-loaded on AXIS A1001 Network Door Controller**
- > **For small systems with basic needs**
- > **Controls who enters where and when**
- > **Intuitive interface**
- > **Supports most reader types, door locks, and door position sensors**



AXIS Entry Manager

System features	
Installation & Configuration	Automatic controller discovery Instant feedback of missing configuration data
Administration	Drag-and-drop operation with flexible assignment of doors and user groups Retrieve credentials from reader Import of users Export access control system reports
Access control	
Configuration	Door configuration with color-coded and printable PIN chart Door configuration verification Multi-factor authentication for door access Customizable card format Locally stored event log configuration
User management	User enrollment with support for card, PIN Search for user
Access management	Create and edit groups combining users, doors and schedules Apply schedule to unlock a door
Manual door control	Lock, unlock, access door
Schedules	Schedule configuration for group access and door unlocking Customization of addition schedules and subtraction schedules
Events & alarms	
Tamper detection	Removal of unit cover/tamper front Removal of unit from wall/tamper back Reader tamper
Event triggers	Tamper detection, Power loss, Network lost, Configuration, Door, Event logger, Hardware, Input signal, Schedule, System, Time
Event actions	Notification via email, HTTP and TCP External output port Status LED
Event log	Configurable by time and topic Alarm acknowledgement Search and filter access control events
General	
Required products	AXIS A1001 Network Door Controller with built-in web-based software
Web browser	Recommended: Latest Chrome™ Supported: Latest Chrome™, Firefox®, Edge™, and Safari®
Languages	English, German, French, Spanish, Italian
Controllers	Recommended: 1-10 Supported: 1-33
Credentials	Up to 400
Event history	30 000 First in First out (FIFO) per system
Readers	Up to 2 readers per controller (Wiegand, RS485 (OSDP) with supported card formats)

Environmental responsibility:

[axis.com/environmental-responsibility](https://www.axis.com/environmental-responsibility)